

STFI12N60M2

N-channel 600 V, 0.395 Ω typ., 9 A MDmesh™ M2 Power MOSFET in an I²PAKFP package

Datasheet - production data





Figure 1: Internal schematic diagram



Features

Order code	rder code V _{DS} R _{DS(on)} max.		I _D	Ртот
STFI12N60M2	600 V	0.450 Ω	9 A	25 W

- Extremely low gate charge
- Excellent output capacitance (C_{OSS}) profile
- 100% avalanche tested
- Zener-protected

Applications

Switching applications

Description

This device is an N-channel Power MOSFET developed using MDmesh™ M2 technology. Thanks to its strip layout and an improved vertical structure, the device exhibits low on-resistance and optimized switching characteristics, rendering it suitable for the most demanding high efficiency converters.

Table 1: Device summary

Order code	Marking	Package	Packing
STFI12N60M2	12N60M2	I²PAKFP	Tube

Contents STFI12N60M2

Contents

1	Electric	al ratings	3
2	Electric	al characteristics	4
	2.1	Electrical characteristics (curves)	6
3	Test cir	cuits	8
4	Packag	e information	9
	4.1	I ² PAKFP (TO-281) package information	9
5	Revisio	n history	11

STFI12N60M2 Electrical ratings

1 Electrical ratings

Table 2: Absolute maximum ratings

Symbol	Parameter	Value	Unit
V_{GS}	Gate-source voltage	±25	V
I _D ⁽¹⁾	Drain current (continuous) at T _{case} = 25 °C		Α
ID	Drain current (continuous) at T _{case} = 100 °C	5.7	A
I _{DM} ⁽²⁾	Drain current (pulsed)	36	Α
P _{TOT}	Total dissipation at T _{case} = 25 °C	25	W
dv/dt ⁽³⁾	Peak diode recovery voltage slope	15	V/ns
dv/dt ⁽⁴⁾	MOSFET dv/dt ruggedness	50	V/IIS
V _{ISO}	Insulation withstand voltage (RMS) from all three leads to external heat sink (t = 1 s; T_C = 25 °C)	2.5	kV
T _{stg}	Storage temperature		°C
T _j	Operating junction temperature	-55 to 150	C

Notes:

Table 3: Thermal data

Symbol	Parameter	Value	Unit
R _{thj-case}	Thermal resistance junction-case	5	900
R _{thj-amb}	Thermal resistance junction-ambient	62.5 °C/	

Table 4: Avalanche characteristics

Symbol	Parameter	Value	Unit
I _{AR} ⁽¹⁾	Avalanche current, repetitive or not repetitive	2.6	Α
E _{AR} ⁽²⁾	Single pulse avalanche energy	117	mJ

Notes:

⁽¹⁾ Limited by maximum junction temperature.

 $^{^{\}left(2\right) }$ Pulse width is limited by safe operating area.

 $^{^{(3)}}$ $I_{SD} \leq 9$ A, di/dt=400 A/µs; $V_{DS(peak)} < V_{(BR)DSS}, \ V_{DD} = 80\% \ V_{(BR)DSS}.$

 $^{^{(4)}} V_{DS} \le 480 V.$

 $^{^{\}left(1\right)}$ Pulse width limited by $T_{jmax}.$

 $^{^{(2)}}$ starting T_{j} = 25 °C, I_{D} = $I_{AR},\,V_{DD}$ = 50 V.

Electrical characteristics STFI12N60M2

2 Electrical characteristics

(T_{case} = 25 °C unless otherwise specified)

Table 5: Static

Symbol	Parameter	Test conditions	Min.	Тур.	Max.	Unit
$V_{(BR)DSS}$	Drain-source breakdown voltage	$V_{GS} = 0 \text{ V}, I_{D} = 1 \text{ mA}$	600			V
	Zoro goto voltago drain	$V_{GS} = 0 \text{ V}, V_{DS} = 600 \text{ V}$			1	
I _{DSS}	Zero gate voltage drain current	$V_{GS} = 0 \text{ V}, V_{DS} = 600 \text{ V},$ $T_{case} = 125 \text{ °C}$			100	μΑ
I _{GSS}	Gate-body leakage current	$V_{DS} = 0 \text{ V}, V_{GS} = \pm 25 \text{ V}$			±10	μΑ
$V_{GS(th)}$	Gate threshold voltage	$V_{DS} = V_{GS}, I_{D} = 250 \mu A$	2	3	4	V
R _{DS(on)}	Static drain-source on- resistance	$V_{GS} = 10 \text{ V}, I_D = 4.5 \text{ A}$		0.395	0.450	Ω

Table 6: Dynamic

Symbol	Parameter	Test conditions	Min.	Тур.	Max.	Unit
C _{iss}	Input capacitance		ı	538	•	
Coss	Output capacitance	$V_{DS} = 100 \text{ V}, f = 1 \text{ MHz},$	ı	29	•	pF
C _{rss}	Reverse transfer capacitance	$V_{GS} = 0 V$	-	1.1	-	ρ.
Coss eq. (1)	Equivalent output capacitance	$V_{DS} = 0$ to 480 V, $V_{GS} = 0$ V	-	106	-	pF
R_{G}	Intrinsic gate resistance	f = 1 MHz, I _D = 0 A	-	7	-	Ω
Q_g	Total gate charge	$V_{DD} = 400 \text{ V}, I_{D} = 9 \text{ A},$	ı	16	•	
Q_gs	Gate-source charge	V _{GS} = 10 V (see <i>Figure 15</i> :	-	2.3	•	nC
Q_{gd}	Gate-drain charge	"Gate charge test circuit")	ı	8.5	1	

Notes:

Table 7: Switching times

Symbol	Parameter	Test conditions	Min.	Тур.	Max.	Unit
t _{d(on)}	Turn-on delay time	$V_{DD} = 300 \text{ V}, I_D = 4.5 \text{ A}$	-	9.2	-	
t _r	Rise time	$R_G = 4.7 \Omega$, $V_{GS} = 10 V$ (see Figure 14: "Switching times	-	9.2	-	
t _{d(off)}	Turn-off delay time	test circuit for resistive load"	ı	56	1	ns
t _f	Fall time	and Figure 19: "Switching time waveform")	-	18	-	

 $^{^{(1)}}$ $C_{oss\ eq.}$ is defined as a constant equivalent capacitance giving the same charging time as C_{oss} when V_{DS} increases from 0 to 80% V_{DSS} .

Table 8: Source-drain diode

Symbol	Parameter	Test conditions	Min.	Тур.	Max.	Unit
I _{SD}	Source-drain current		ı		9	Α
I _{SDM} ⁽¹⁾	Source-drain current (pulsed)		-		36	Α
V _{SD} ⁽²⁾	Forward on voltage	$V_{GS} = 0 \text{ V}, I_{SD} = 9 \text{ A}$	ı		1.6	V
t _{rr}	Reverse recovery time	$I_{SD} = 9 \text{ A}, \text{ di/dt} = 100 \text{ A/}\mu\text{s},$	ı	284		ns
Q_{rr}	Reverse recovery charge	V _{DD} = 60 V (see Figure 16: "Test circuit for inductive	ı	2.4		μC
I _{RRM}	Reverse recovery current	load switching and diode recovery times")	-	17		Α
t _{rr}	Reverse recovery time	$I_{SD} = 9 \text{ A}, \text{ di/dt} = 100 \text{ A/}\mu\text{s},$	-	404		ns
Q _{rr}	Reverse recovery charge	$V_{DD} = 60 \text{ V}, T_j = 150 ^{\circ}\text{C} \text{ (see}$ Figure 16: "Test circuit for	-	3.5		μC
I _{RRM}	Reverse recovery current	inductive load switching and diode recovery times")	-	17.5		Α

Notes:

⁽¹⁾ Pulse width is limited by safe operating area.

 $^{^{(2)}}$ Pulse test: pulse duration = 300 $\mu s,$ duty cycle 1.5%.

2.1 Electrical characteristics (curves)




Figure 5: Transfer characteristics

(A)

16

V_{DS} = 11 V

12

8

4

0

0


2


4

6

8

V_{GS} (V)





STFI12N60M2 Electrical characteristics







Figure 9: Normalized gate threshold voltage vs temperature

V_{SS(III)}
1.10
1.00
1_D = 250 μA
0.90
0.80
0.70
-50 0 50 100 T_j(°C)

Figure 10: Normalized on-resistance vs temperature R_{DS(on)} (norm.) GIPG110515MQF1LRON V_{GS} = 10 V 2.2 1.8 1.4 1.0 0.6 0.2 -75 -25 25 75 125 T_i (°C)








Test circuits STFI12N60M2

3 Test circuits








Figure 16: Test circuit for inductive load switching and diode recovery times






Figure 17: Unclamped inductive load test circuit

Figure 18: Unclamped inductive waveform V(BR)DSS





STFI12N60M2 Package information

4 Package information

In order to meet environmental requirements, ST offers these devices in different grades of ECOPACK® packages, depending on their level of environmental compliance. ECOPACK® specifications, grade definitions and product status are available at: **www.st.com**. ECOPACK® is an ST trademark.

4.1 I²PAKFP (TO-281) package information

Α Н В D1 97 11 D -F1 (x3) F(x3)Ε G 8291506 Re v. C

Figure 20: I²PAKFP (TO-281) package outline

Table 9: I²PAKFP (TO-281) mechanical data

STFI12N60M2

Dim	,	mm	
Dim.	Min.	Тур.	Max.
А	4.40	-	4.60
В	2.50		2.70
D	2.50		2.75
D1	0.65		0.85
E	0.45		0.70
F	0.75		1.00
F1			1.20
G	4.95		5.20
Н	10.00		10.40
L1	21.00		23.00
L2	13.20		14.10
L3	10.55		10.85
L4	2.70		3.20
L5	0.85		1.25
L6	7.50	7.60	7.70

STFI12N60M2 Revision history

5 Revision history

Table 10: Document revision history

Date	Revision	Changes
22-May-2015	1	First release.

IMPORTANT NOTICE - PLEASE READ CAREFULLY

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2015 STMicroelectronics - All rights reserved

